



For load test for various
inverters such as inverter for
Fuel Cell power generation,
UPS inverter, inverter for
photovoltaic generation, and
transformer

- Parallel operation expands the load capacity
Up to 5 units can be operated in parallel
Max. 5KW, 50Arms
- Supports single-phase 3-wire method,
3-phase 3-wire method
Equipped with tracking operation function



NEW

AC ELECTRONIC LOAD PCZ1000A

- Maximum input load power: 1000W
- Input voltage range: 14V to 280V(rms)
- Input current range: 0 to 10A(rms)
- Input frequency range: 45 to 65Hz

Constant Current/Constant Resistance/Constant Power mode provided.
Useful Crest Factor function is equipped.

PCZ1000A is an AC electronic load that enables you to perform load simulation for various inverters and transformers.

In addition to the resistive loads generally used in tests, it is capable of simulating capacitor-input rectifier loads.


The instrument supports input up to 1000W and is equipped with 3 operation modes - Constant Current, Constant Resistance, and Constant Power.

Current waveform resemble to sine wave can be output constantly without effect by voltage waveform at each mode. Moreover, the instrument is equipped with Crest Factor function that is suitable for simulating current load test for switching power supply.


This instrument provides improved operability through CPU control and enables external control and read-back via RS-232C.

Crest Factor Function [1.4 to 4.0]


Facilitating load tests for peak or harmonic currents helps reduce design and labor time and cost as well as improve the quality of the unit under test [- Voltage waveform - Current waveform]




▲ C.F setting value1.4



▲ C.F setting value2.0



▲ C.F setting value3.0



▲ C.F setting value4.0

Specifications

Input Rating (AC)	Operating Voltage*1	14 to 280Vrms 20 to 400Vpeak	
	Maximum Current*2	10Arms 40Apeak	
	Maximum Power*3	1000W	
	Frequency	45 to 65Hz	
	Minimum Operation Starting Voltage*4	3Vpeak	
Constant Current (C.C) mode *5	Setting Range	0 to 10Arms	
	Setting Accuracy*9	Within ± (1% of set + 0.1A)	
	Setting Resolution	10mArms	
	Stability	Line variations *10	Within ± 10mArms
		Input voltage variations*11	Within ± 100mArms
Temperature Coefficient (at rated current)	200PPM/°C (typical)		
Constant Resistance (C.R) mode *6	Setting Range	H range (Full current at 10V)	1 Ω to 1k Ω 1S to 1mS *20
		L range (Full current at 100V)	10 Ω to 10k Ω 0.1S to 0.1mS *20
	Setting Resolution	H range	1mS*20
		L range	0.1mS*20
	Setting Accuracy (in current terms) *9, *12	Within ± (2% of set + 0.2A)	
	Stability	Input voltage variations*13	Within ± 10%
Constant Power (C.P) mode *7	Setting Range	50W to 1000W	
	Setting Accuracy *9, 14	Within ± 5% of set	
	Setting Resolution	1W	
	Input voltage variations*15	Within ± 5%	
Crest Factor (C.F)function *8	Setting Range	1.4 to 4.0	
	Resolution	0.1	
Master-slave parallel operation	Up to 5 units including master unit		
Tracking function	Same current as master unit passes to slave unit		
Ammeter (RMS display mode)	Number of display digits (full scale)	10.00Arms	
	Accuracy*9	Within ± 1% of FS	
Ammeter (PEAK display mode)	Number of display digits (full scale)	40.0Apeak	
	Accuracy*9	Within ± 2% of FS	
Voltmeter	Number of display digits (full scale)	300.0Vrms	
	Accuracy*9	Within ± 1% of FS	
Protection function	Peak Overcurrent protection (POCP) *16	Approx.48Apeak	
	Overcurrent protection (OCP) *17	Approx.11.5Arms	
	Overvoltage protection (OVP) *16	Approx.470Vpeak	
	Overpower protection (OPP) *17	Approx.1150W	
	Overheat protection (OHP) *18	—	
Internal power element protection (FUSE BRK)	Cut off internal fuse		
Input Power (AC)	Voltage range (nominal value) *19	1	90 to 110 (100) Vrms
		2	108 to 132 (120) Vrms
		3	180 to 220 (200) Vrms
		4	216 to 250 (240) Vrms
	Frequency	50 / 60Hz	
Power consumption (Apparent power)	MAX220VA		
Withstanding voltage	Primary — Chassis	1500Vac, 1 minute	
	Primary — Load input terminal	1500Vac, 1 minute	
	Load input terminal — Chassis	500Vac, 1 minute	
Insulation resistances	Primary — Chassis	DC1000V, 20M Ω and over	
	Primary — Load input terminal	DC1000V, 20M Ω and over	
	Load input terminal — Chassis	DC1000V, 20M Ω and over	
Temperature and humidity range	Operating temperature range	0 to 40°C	
	Operating humidity range	20 to 85% rh (no condensation)	
	Storage temperature range	— 25 to 70°C	
	Storage humidity range	90% RH or less (no condensation)	
Dimensions(Chassis)	430W × 400D × 128Hmm		
Weight	Approx.22kg		

- *1 Input voltage range in which rated input current can flow
- *2 For an input voltage of 100Vrms or greater, the maximum current is derated at the rated input power (1000W)
- *3 For an input voltage of 100Vrms or less, the maximum power is limited by the rated input current (10Arms).
- *4 Minimum input voltage at which the input current starts to flow.
- *5 The input current waveform does not change with changes in the input voltage waveform.
The rms value of the input current is kept constant (response rate: approximately 1s)
(Response rate: Time required to reach ±10% of the steady value (value reached 5 seconds or more after state change))
- *6 The input current waveform does not change with changes in the input voltage waveform..
This mode allows an input current (rms value) proportional to the rms value of the input voltage to flow (response rate: approximately 1s)
- *7 The input current waveform does not change with changes in the input voltage waveform.
This mode allows an input current (rms value) inversely proportional to the rms value of the input voltage to flow (response rate: approximately 1s).
- *8 Varies the angular width of the current at the approximate input voltage peak, based on the sinusoidal current waveform.
- *9 At room temperature (23±5°C)
- *10 Changes in the input current when variations in the rated voltage range are given at an input voltage of 100Vrms and an input current of 10Arms, based on the nominal value of the input line voltage.
- *11 Changes in the input current when the input voltage is changed from 10Vrms to 280Vrms at an input current of 3.57Arms (rating at an input voltage of 280Vrms)
- *12 At an input voltage 100Vrms
- *13 Changes in the resistance value when the input voltage is varied from 10Vrms to 100Vrms at an input current of 0.5A or more.
- *14 At an input voltage of 100Vrms
- *15 Changes in the power value when the input voltage is varied from 10Vrms to 100Vrms
- *16 Turns off [LOAD] KEY within 20ms
- *17 Turns off [LOAD] KEY within 3s
- *18 Detects the internal heat sink surface temperature to turn off the [LOAD] key
- *19 Switching
- *20 S represents unit of conductance (siemens)
Conductance [S] = 1 / Resistance value [Ω]
Conductance [S] × Input voltage [V] = Load current [A]

Options

- Rack mount bracket
 - KRB3 (Inch size, EIA standard compatible rack)
 - KRB150 (Metric size, JIS standard compatible rack)
- Parallel operation cable
 - PC01 PCZ1000A



KIKUSUI ELECTRONICS CORPORATION

1-1-3, Higashiyamata, Tsuzuki-ku, Yokohama, 224-0023, Japan

Phone: (+81) 45-593-7570, Facsimile: (+81) 45-593-7571, www.kikusui.co.jp

●Affiliate companies:



KIKUSUI AMERICA, INC.

1744 Rollins Road, Burlingame, CA 94010
Phone: (650) 259-5900, Facsimile: (650) 259-5904
Toll Free: (1-800-KIKUSUI), www.kikusui.us



KIKUSUI TRADING (SHANGHAI) Co., Ltd.

Room D, 11F, Yonghua Bldg., No.138, Pudong Road,
Pudong New District, Shanghai City
Phone: 021-5887-9067, Facsimile: 021-5887-9069, www.kikusui.cn

For our local sales distributors and representatives, please refer to "sales network" of our website.

Printed in Japan

■Distributor:

- All products contained in this catalogue are equipment and devices that are premised on use under the supervision of qualified personnel, and are not designed or produced for home-use or use by general consumers. ■ Specifications, design and so forth are subject to change without prior notice to improve the quality. ■ Product names and prices are subject to change and production may be discontinued when necessary. ■ Product names, company names and brand names contained in this catalogue represent the respective registered trade name or trade mark. ■ Colors, textures and so forth of photographs shown in this catalogue may differ from actual products due to a limited fidelity in printing. ■ Although every effort has been made to provide the information as accurate as possible for this catalogue, certain details have unavoidably been omitted due to limitations in space. ■ If you find any misprints or errors in this catalogue, it would be appreciated if you would inform us. ■ Please contact our distributors to confirm specifications, price, accessories or anything that may be unclear when placing an order or concluding a purchasing agreement.

Issue:2007020.3K11